

DCN-CONCS Concentus Channel Selector

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Low susceptibility to mobile phones
- ▶ Compact, attractive delegate unit
- ▶ Built-in, fold-away, flat-panel loudspeaker
- ▶ Five voting buttons
- ▶ Cable connections located underneath the unit

The DCN-CONCS is similar to the DCN-CON Standard Delegate Unit, but includes a built-in language channel selector. This makes it suitable for conferences where more than one language is used and simultaneous interpretations are available. The channel selector includes up and down select keys and a 2-digit display with backlighting, enabling rapid selection of the required language channel. Channel selection is automatically limited to the number of language channels available. The flat-panel loudspeaker offers superior acoustics with minimal feedback, thus increasing intelligibility. When the unit is not being used, the loudspeaker panel conveniently folds down.

Functions

Controls and Indicators

- Channel selector with channel number display with back lighting and channel select keys (up/down)
- Headphone volume control on each side of the unit
- Built-in fold-away flat-panel loudspeaker, automatically muted if a microphone is on
- Microphone 'on/off' or 'request-to-speak' button
- 'Microphone-on' indicator at the top of the loudspeaker
- Tri-color indicator above the microphone button:
 - Red microphone on indicator

- Green 'Request-to-speak' confirmation indicator
- Yellow 'VIP' indicator. 'VIP' is lit when the delegate unit is part of the notebook, which is only available when PC control software is used
- Five voting buttons with yellow LED confirmation indicators These can be used to register:
 - PRESENT, YES (+), NO (-), ABSTAIN (X), (parliamentary voting)
 - Numerals: 1 to 5 (multiple choice or opinion polls)
 - Rating scale: - -, -, 0, +, ++ (audience response)

Interconnections

- Socket for pluggable microphone
- 2 m (78.7 in) cable terminated in a molded six-pole circular connector
- Socket for external microphone or headset microphone
- Six-pole circular connector for loop-through connections
- Eight-pole modular jack connector for Intercom Handset LBB 3555/00 and external present and fraud contact e.g. a fingerprint reader
- Left and right 3.5 mm (0.14 in) stereo jack type headphones sockets
- Connection 3.5 mm (0.14 in) for external microphone or stereo jack type headset microphone

Certifications and approvals

Region	Certification
Europe	CE

Technical specifications

Electrical

Headphone connection	
Frequency response	30 Hz to 20 kHz
Load impedance	> 32 ohm
Output power	2 x 15 mW/32 ohm
Headset connection	
Frequency response	30 Hz - 20 kHz
Load impedance	> 32 ohm
Output power	2 x 15 mW/32 ohm
Nominal microphone input level	7 mVrms
Overload microphone input level	> 124 mVrms
Interface data	
Recommended external microphone type (or headset microphone)	
Element	Electret-condenser
Polar pattern	Omni directional
Operating voltage	5 VDC
Sensitivity	62 dB at 1200 ohm (0 dB = 1 V/mbar at 1 kHz)
Frequency response	100 Hz to 14 kHz
Connector	3.5 mm (0.14 in) jack mono or stereo

Mechanical

Mounting	Tabletop (portable or fixed mounting) and flush mounting
Dimensions (H x W x D)	(without microphone)
Tabletop	50 x 275 x 155 mm 2.0 x 10.8 x 6.1 in)
Flush mounted	30 x 275 x 155 mm (1.2 x 10.8 x 6.1 in)
Weight	1.4 kg (3.1 lb)

Color top	Charcoal (PH 10736) with silver (RAL 9022) panel
Color base	Charcoal (PH 10736)

Ordering information

DCN-CONCS Concentus Channel Selector

pluggable microphone, voting, channel select, 2 headphone sockets, microphone to be ordered separately

Order number **DCN-CONCS**

DCN-MICS Pluggable Short Microphone

length 310 mm (12.2 inch), silver

Order number **DCN-MICS**

DCN-MICL Pluggable Long Microphone

length 480 mm (18.9 inch), silver

Order number **DCN-MICL**

Represented by:

Americas:

Bosch Security Systems, Inc.
12000 Portland Avenue South
Burnsville MN 55337, USA
Phone: +1-800-392-3497
Fax: +1-800-955-6831
audiosupport@us.bosch.com
www.boschsecurity.com

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
al.securitysystems@bosch.com
www.boschsecurity.com